

TROUBLE FREE CHANGE OVER OF POWER

T-30 & T-57 TRANSFER SWITCHES

For 30 and 50 Amp/120 Vac electrical systems.

The WFCO T-30 and T-57 auto transfer switches are designed to provide trouble-free changeover of power between shore power and generator. T-57 is designed for 50 Amp AC service, where as the T-30 transfer switch is used for 30 Amp AC services.

The T-30 can be installed onto the back of WFCO 8900 Series Power Centers. The T-57 mounts easily to a flat surface. The compact design allows easy placement. The T-30 and T-57 are engineered for safe, reliable performance.

The unit's DC coil prevents AC "chatter" noise and drop-out in low voltage conditions.

Accidental coupling of power from or to shore line and generator is prevented by a "make before break" configuration.



Transfer Switches Specifications

T-30 Transfer Switch

AC Rating: 120 volts/30 amps

Dimensions: 5" W; 5-5/8" H; 5" D

Weight: 4.75 lbs.

Installations:

Attaches to back of WFCO 8900 Series Power Centers.

T-57 Transfer Switch

AC Rating: 120 volts/50 amps

Dimensions: 8.1" W; 10.1" H; 5.5" D

Weight: 5.5 lbs.

Installations:

Attaches to back of WFCO 8900 Series Power Centers; also mounts on flat surfaces as a stand-alone in conjunction with any distribution panel.

All models are UL, cUL approved and FCC Class B compliant. Two-Year Limited Product Warranty



A NEW WORLD OF POWER IDEAS.



Distributed by CHENG USA INC.

2021 Aeroplex Drive North
Elkhart, IN 46514

Phone: (574) 294-8997

Fax: (574) 294-8698

www.wfcoelectronics.com



AUTOMATIC TRANSFER SWITCHES

Item: Specifications:

| Model Number | T-30 | T-57 |
|----------------|---------------|-------------------|
| Input Voltage | 120 Vac 60 Hz | 120/240 Vac 60 Hz |
| Input Current | 30 A | 50 A |
| Voltage Output | 120 Vac 60 Hz | 120/240 Vac 60 Hz |
| Output Current | 30 A | 50 A |

Safety Features/Protections:

| | | |
|-------------------|-----|-----|
| Shore Power input | Yes | Yes |
| Generator input | Yes | Yes |

Shipping:

| | | |
|---------------------|--------------|---------------------|
| Outside Dimensions: | 5" x 5" x 6" | 8.1" x 10.1" x 5.5" |
| Weight | 4.5 lbs. | 10 lbs. |

Installation:

| | | |
|----------------|----------------------|----------------------|
| Knockout Holes | 3 | 5 |
| Knockout Sizes | 2 x 7/8" 1 x 1.0" | 4 x 1.0" 1 x 2.0" |

Standards:

| | | |
|-------------------|-----|-----|
| Complies with FCC | Yes | Yes |
|-------------------|-----|-----|



WF-8930/50
Distribution Panel
30A/50A Service



T-57



T-30



WF-89xxANP/T30
30A Transfer Switch
(option)

Specifications are subject to change without notice or obligation.

website: <http://www.wfcoelectronics.com>