

# SPECIFICATIONS

<b>MODEL NUMBER</b>	<b>41001.611</b>		
<b>NOMINAL BTU COOL/HEAT</b>	<b>12,000</b>		
<b>VOLTS/PHASE/HERTZ*</b>	<b>115/1/60</b>		
<b>FLA COMP/MOTOR</b>	<b>9.5/2.5</b>		
<b>LRA COMPRESSOR</b>	<b>54</b>		
<b>WIRE SIZE**</b>	<b>12 AWG Copper Conductor</b>		
<b>CIRCUIT PROTECTION</b>	<b>15 Amp Time Delay Fuse or</b>		
	<b>15 Amp HACR Circuit Breaker</b>		
<b>REFRIGERANT</b>	<b>R-22</b>		
<b>SYSTEM REFRIGERANT CHARGE</b>	<b>24.5 oz</b>		
<b>SIZE (INCHES)</b>	<b>width</b>	<b>height</b>	<b>depth</b>
	<b>22</b>	<b>14.5</b>	<b>20.5</b>
<b>INSTALLED WEIGHT</b>	<b>70 Pounds</b>		
<b>GENERATOR ***</b>			
1 Unit	<b>2.8 KW</b>		
2 Units	<b>4.0 KW</b>		

\* Maximum unit performance achieved at full rated voltage.

\*\* For lengths over 24 ft., consult the National Electrical Code.

\*\*\* The Dometic Corp. gives **general** guidelines for generator requirements. These guidelines come from experiences people have had in actual applications. When sizing the generator, the **total** power usage of your recreational vehicle must be considered. Also keep in mind generators lose power at high altitudes and from lack of maintenance.